

Show is run from subs, program as follows:

- Sub 1: Channels 1, white wash L+R. Focus DSL / DSR across centre blue dashed oval, head
- Sub 2: Channels 2, white wash DS L to R oval
- Sub 3: Channels 3, Focus orange backlight L+R crossing over blue dashed oval
- Sub 4: Channels 4, Orange backlight CTR
- Sub 5: Channels 6, 9, blue/violet audience ring outside oval
- Sub 6: Channels 8, 7 star gobos along dashed oval line, ca 3m diameter each
- Sub 7: Channels 5, mirrorball spot
- Sub 8: CH10, Top of SR Box

If board only has 6 subs: Run Sub 7 and 8 from preset channels instead

Key	
	Color
	Channel
	Profile ca 23-50
	Profile ca 15-32
	Fresnel
	par64/CP62 (or Fresnel)

Colour is toured, but can be replaced as follows:
 R359 = L180, L170 or any medium blue-violet
 R20 = L020 or L179 or any medium orange

Gobos 4x B size Rosco 77112 Stars or replace with similar or dots




NOTES

THIS IS MEANT TO BE FLEXIBLE –ADAPT AS NECESSARY OR PRE-RIGGED

- rig height 4–5 m
- Rig patched down to a minimum of 9 channels
- pairing only as indicated
- all Fresnels c/w barndoors
- all Par64 CP62 or replace with Fresnels as shown in layout B

Only B gobos toured – advise if unavailable

Space needs full B/O, wood / light floor preferred
 Masking black box or white walls



Shiny

Turned on its Head
 Generic LX plan

Company contact Liz Clark: lizclark_dance@hotmail.com